



BEAMZ
MADE
EAZY

150.618 V1.0

BBP12

QUICK START GUIDE

CONTROL MENU

MENU			DESCRIPTION
_100	_100	0-100	Battery level indicator
d001	A001	001-512	DMX512 address setting
Set	5CH	5/9	DMX Channel
	uDon	on/oF	Wireless DMX switch
	rFon	on/oF	Remote control switch
	S_FA	FA/SL	DMX512 dimming speed SL: slow dimming; FA: fast dimming
	d_oF	Ho/oF	DMX signal loss processing mode setting: Ho: keep the last DMX signal state; oF: Turn off all LEDs
Led	r255	000-255	Red dimming, 0-100%
	G255	000-255	Green dimming, 0-100%
	b255	000-255	Blue dimming, 0-100%
	L255	000-255	Lime dimming, 0-100%
	A255	000-255	Amber dimming, 0-100%
FEct	CL01	00-32	Select 1 of 32 static colors
	CC15	00-15	Color jumping, speed from slow to fast
	dE15	00-15	Color Gradual change, speed from slow to fast
	CP15	00-15	Color Pulse change, speed from slow to fast
	F000	000-255	Strobe, speed from slow to fast

DMX CHANNELS

5 CHANNELS

CHANNEL	FUNCTION	VALUE	SETTING
1	RED	000-255	Red dimmer 0-100%
2	GREEN	000-255	Green dimmer 0-100%
3	BLUE	000-255	Blue dimmer 0-100%
4	LIME	000-255	Lime dimmer 0-100%
5	AMBER	000-255	Amber dimmer 0-100%

9 CHANNELS

CHANNEL	FUNCTION	VALUE	SETTING
1	MASTER DIMMER	000-255	Master dimmer, 0-100%
2	RED	000-255	0-100%
3	GREEN	000-255	0-100%
4	BLUE	000-255	0-100%
5	LIME	000-255	0-100%
6	AMBER	000-255	0-100%
7	MASTER STROBE	000-255	Slow to fast
8	MANUAL	000-050	No function
		051-100	Built-in color selection, controlled by CH9
		101-150	Color jumping
		151-200	Color Gradual change
		201-255	Color Pulse change
9	SPEED	000-255	Slow to fast



BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.



BEAMZLIGHTING.COM