



BEAMZ
MADE
EAZY

155.095_155.096 V1.0

BTK050Z

QUICK START GUIDE

CONTROL MENU

MENU			DESCRIPTION
DMX ADDR	x001-x512		DMX address setting
ROTATY DIM	→		
	Bright	000-255	Dimmer by manual knob
	CCT	2700K-6500K	Adjust color temperature by manual knob
BRIGHT	000-255		Dimmer
CCT	2700K-6500K		color temperature
DMX KEEP	OFF		Release DMX when signal lost
	ON		Hold DMX when signal lost
BACK LIGHT	OFF		Oled display backlight off
	ON		Oled display backlight on
DMX PRIO	OFF		Set manual control function priority
	ON		Set DMX signal priority
DMX MODE	2CH		2 DMX channels mode
	3CH		3 DMX channels mode
TEMP	XX°C		Current temperature of LED source
SYSTEM INF	→		System information
	SN	***	Software name
	Ver	***	Software version

DMX CHANNELS

2 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	COOL WHITE	000-255	Dimmer 0-100%
2	WARM WHITE	000-255	Dimmer 0-100%

3 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	MASTER DIMMER	000-255	Dimmer 0-100%
2	CCT	000-255	Color temperature setting
3	STROBE	000-255	Strobe from slow to fast



BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT



offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!

