



BEAMZ
MADE
EAZY

150.190 V1.1

LCB246IP

QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION	
AUTO MODE	Auto	Sp 1-10	Auto Speed 1-10 (slow->fast)
		St 0-9	Strobe (Slow->fast)
DMX MODE	Addr	6 CH	A001-A507
		8 CH	A001-A505
		11CH	A001-A502
		48CH	A001-A465
		52CH	A001-A461
SHOW	Shou	Sh 1- 53	Program Show 1-53
		Sp 1-10	Program Speed 1-10 (slow->fast)
		St 0-9	Program Flash 0-9 (slow->fast)
SLAVE	SLAV	Slave	Slave (F rom the machine, automatically identify the host)
EDIT COLOR	Colo	R000-255	Red (0-100%)
		G000-255	Green (0-100%)
		B000-255	Blue (0-100%)
		U000-255	White (0-100%)
		A000-255	Amber (0-100%)
		P000-255	UV (0-100%)
		St0-9	LED Strobe (slow->fast)
STATIC COLORS	StAt	CL01-CL23	Static color (The 23 static colors are optional)
		St0-9	LED Strobe (slow->fast)
PRODUCT SET	Set	dis	10s 20s 30s 60s On Set the display panel backlight time, 10 seconds to continuous light, factory default of 10 seconds
		temP	50-70°C Protection temperature setting, protection within 50-70°C, beyond which range begins to reduce the output power (factory setting 60)°C)
		dir	---> <--- Set the light direction to the right Set the light direction to the left
		InFr	on oFF Remote control function is set on Remote control function is set off
		Send	Yes Send One-click set transmission function to send the current lamp channel mode and temperature protection value to other lamps connected to this lamp.(No other controller on the line)
		Ver	Vxxx Software version
		Temp	XX C Current lamp board temperature (degrees °C), if the temperature detection line fails, boot prompt -RT-, the menu display error

DMX CHANNELS

6 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	RED	000-255	Red 0-100%
2	GREEN	000-255	Green 0-100%
3	BLUE	000-255	Blue 0-100%
4	WHITE	000-255	White 0-100%
5	AMBER	000-255	Amber 0-100%
6	UV	000-255	UV 0-100%

8 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	MASTER DIMMER	000-255	Master dimmer 0-100%
2	STROBE	000-009	No Function
		010-255	Strobe from slow to fast
3	RED	000-255	Red 0-100%
4	GREEN	000-255	Green 0-100%
5	BLUE	000-255	Blue 0-100%
6	WHITE	000-255	White 0-100%
7	AMBER	000-255	Amber 0-100%
8	UV	000-255	UV 0-100%

11 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	MASTER DIMMER	000-255	Master dimmer 0-100%
2	RED	000-255	Red 0-100%
3	GREEN	000-255	Green 0-100%
4	BLUE	000-255	Blue 0-100%
5	WHITE	000-255	White 0-100%
6	AMBER	000-255	Amber 0-100%
7	UV	000-255	UV 0-100%
8	STROBE	000-009	No Function
		010-255	Strobe from slow to fast
9	EFFECT	000-003	No Function
		004-007	Effect 1
		008-011	Effect 2
		012-015	Effect 3
			
		204-207	Effect 51
		208-211	Effect 52
		212-215	Effect 53
		216-255	Chase effect
10	SPEED	000-255	Effect speed slow to fast
11	BACKGROUND COLOUR	000-255	Background colour selection when channel 9 is valid

48 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	RED	000-255	Segment 1 Dimmer Red (0-100%)
2	GREEN	000-255	Segment 1 Dimmer Green (0-100%)
3	BLUE	000-255	Segment 1 Dimmer Blue (0-100%)
4	WHITE	000-255	Segment 1 Dimmer White (0-100%)
5	AMBER	000-255	Segment 1 Dimmer Amber (0-100%)
6	UV	000-255	Segment 1 Dimmer UV (0-100%)
.....			
43	RED	000-255	Segment 8 Dimmer Red (0-100%)
44	GREEN	000-255	Segment 8 Dimmer Green (0-100%)
45	BLUE	000-255	Segment 8 Dimmer Blue (0-100%)
46	WHITE	000-255	Segment 8 Dimmer White (0-100%)
47	AMBER	000-255	Segment 8 Dimmer Amber (0-100%)
48	UV	000-255	Segment 8 Dimmer UV (0-100%)

52 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	RED	000-255	Segment 1 Dimmer Red (0-100%)
2	GREEN	000-255	Segment 1 Dimmer Green (0-100%)
3	BLUE	000-255	Segment 1 Dimmer Blue (0-100%)
4	WHITE	000-255	Segment 1 Dimmer White (0-100%)
5	AMBER	000-255	Segment 1 Dimmer Amber (0-100%)
6	UV	000-255	Segment 1 Dimmer UV (0-100%)
.....			
43	RED	000-255	Segment 8 Dimmer Red (0-100%)
44	GREEN	000-255	Segment 8 Dimmer Green (0-100%)
45	BLUE	000-255	Segment 8 Dimmer Blue (0-100%)
46	WHITE	000-255	Segment 8 Dimmer White (0-100%)
47	AMBER	000-255	Segment 8 Dimmer Amber (0-100%)
48	UV	000-255	Segment 8 Dimmer UV (0-100%)
49	STROBE	000-009	No Function
		010-255	Strobe from slow to fast
50	EFFECT	000-003	No Function
		004-007	Effect 1
		008-011	Effect 2
		012-015	Effect 3
			
		204-207	Effect 51
		208-211	Effect 52
		212-215	Effect 53
		216-255	Chase effect
51	SPEED	000-255	Effect speed slow to fast
52	BACKGROUND COLOUR	000-255	Background colour selection when channel 9 is valid









BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.



BEAMZLIGHTING.COM