



BEAMZ
MADE
EAZY

150.434 V1.0

COBRA 160

QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION
MX ADDR	A001-A512	DMX address setting 001-512
CHND	17CH	DMX channel
SLND	DMX/AUTO/SOUND	Running mode
REVERS PAN	Yes/ No	Reverse Pan
REVERS TILT	Yes/ No	Reverse Tilt
SENE	000-100	Sound sensitive
LED	On / Off	Black light
DISPLAY	Yes/ No	Display reverse
TEMP	XXX	Device's temperature
VER	V100	Software version
FAET	Yes/ No	Restore to factory set

DMX CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION		
1	PAN	000-255			
2	PAN FINE	000-255			
3	TILT	000-255			
4	TILT FINE	000-255			
5	P/T SPEED	000-255	Speed from fast to slow		
6	ROTATING MOTOR	000-059	0-360 degree rotation		
		060-119	Clockwise rotate from slow to fast		
		120-179	Counter-clockwise rotate from slow to fast		
		180-255	Clockwise and Counter-clockwise Rotate alternately from slow to fast		
7	COLOR	001-015	White		
		016-031	Color 1		
		032-047	Color 2		
		048-063	Color 3		
		064-079	Color 4		
		080-095	Color 5		
		096-111	Color 6		
		112-127	Color 7		
		128-191	Color Wheel clockwise rotate from fast to slow		
		192-255	Color Wheel counter-clockwise rotate from slow to fast		
		8	GOBO	000-007	White
				008-015	Gobo 1
016-023	Gobo 2				
024-031	Gobo 3				
032-039	Gobo 4				
040-047	Gobo 5				
048-055	Gobo 6				
056-063	Gobo 7				
064-073	Gobo 7 shake from slow to fast				
074-083	Gobo 6 shake from slow to fast				
084-093	Gobo 5 shake from slow to fast				
094-103	Gobo 4 shake from slow to fast				
104-113	Gobo 3 shake from slow to fast				
114-123	Gobo 2 shake from slow to fast				
124-127	Gobo 1 shake from slow to fast				
128-191	Gobo Wheel clockwise rotate from fast to slow				
192-255	Gobo Wheel counter-clockwise rotate from slow to fast				
9	DIMMER	000-255	Dimmer from dark to bright		
10	STROBE	000	No function		
		001-255	Strobe from slow to fast		
11	SPOT LED	000-255	Spot from dark to bright		
12	B-EYE RED	000-255	B-EYE Red from dark to bright		
13	B-EYE GREEN	000-255	B-EYE Green from dark to bright		
14	B-EYE BLUE	000-255	B-EYE Blue from dark to bright		
15	B-EYE WHITE	000-255	B-EYE White from dark to bright		
16	MACRO FUNCTION	000-049	CH1-CH14 valid		
		050-149	Auto running		
		150-255	Sound control		
17	RESET	000-240	No function		
		241-255	All reset after 5s		

*In DMX Mode, If there is no DMX Signal, the first digital will flash, when the display is off, the middle position of last digital will flash.



BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.

