



BEAMZ
MADE
EAZY

153.292 V1.0

BS960

QUICK START GUIDE

CONTROL MENU

MENU			DESCRIPTION
DMX ADDR	A001-A512		DMX address setting
CHANNEL	CH03-CH39		Select channel
MODE1	M000-M083	84 kinds of effects	Select three-in-one built-in effects
SPEED	S000-S255		Adjust the running speed of the three-in-one effect
EFFECTS	M000-M040	41 built-in effects of middle white light	Select built-in effects
SPEED	S000-S255		Adjust the running speed of the built-in effect
SOUND			Voice mode
RED	R000-R255		Red brightness adjustment
GREEN	G000-G255		Green brightness adjustment
BLUE	B000-B255		Blue brightness adjustment
WHITE	W000-W255		White brightness adjustment
TEMPERATURE	T000		Display temperature, If 10K thermistor not installed, T000 is displayed.

DMX CHANNELS

4CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	RED	000-255	Red bead linear dimming
2	GREEN	000-255	Green bead linear dimming
3	BLUE	000-255	Blue bead linear dimming
4	WHITE	000-255	White bead linear dimming

11CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1		000-255	Total dimming
2		000-255	Three in one stroboscopic
3		000-255	Three in the first mock exam
4		000-255	Three in the first mock exam speed
5		000-255	Red linear dimming
6		000-255	Green linear dimming
7		000-255	Blue linear dimming
8		000-255	White stroboscopic
9		000-255	White light mode
10		000-255	White light mode speed
11		000-255	White light linear dimming

32CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1		000-255	Section 1 three in one red light linear dimming
2		000-255	Section 1 three in one green light linear dimming
3		000-255	Section 1 three in one blue light linear dimming
4		000-255	Section 2 three in one red light linear dimming
5		000-255	Section 2 three in one green light linear dimming
6		000-255	Section 2 three in one blue light linear dimming
...	
22		000-255	Section 8 three in one red light linear dimming
23		000-255	Section 8 three in one green light linear dimming
24		000-255	Segment 8 three in one blue light linear dimming
25		000-255	Section 1 white light bead linear dimming
26		000-255	Linear dimming of section 2 white light bead
27		000-255	Section 3 white light bead linear dimming
28		000-255	Section 4 white light bead linear dimming
29		000-255	Section 5 white light bead linear dimming
30		000-255	Section 6 white light bead linear dimming
31		000-255	Section 7 white light bead linear dimming
32		000-255	Section 8 white light bead linear dimming

39CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1		000-255	Total dimming
2		000-255	Three in one stroboscopic
3		000-255	The first mock exam is the first mock exam. Three in one mode
4		000-255	Three in the first mock exam speed
5		000-255	Section 1 three in one red light bead linear dimming
6		000-255	Section 1 three in one green light bead linear dimming
7		000-255	Section 1 three in one blue light bead linear dimming
...	
26		000-255	Section 8 three in one red light bead linear dimming
27		000-255	Section 8 three in one green light bead linear dimming
28		000-255	Segment 8 three in one blue light bead linear dimming
29		000-255	White stroboscopic
30		000-255	White light mode
31		000-255	White light mode speed
32		000-255	Section 1 white light bead linear dimming
33		000-255	Linear dimming of section 2 white light bead
34		000-255	Section 3 white light bead linear dimming
35		000-255	Section 4 white light bead linear dimming
36		000-255	Section 5 white light bead linear dimming
37		000-255	Section 6 white light bead linear dimming
38		000-255	Section 7 white light bead linear dimming
39		000-255	Section 8 white light bead linear dimming



BEAMZ

**YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT**



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.

