



155.109_155.113 V1.2

BTM100WW & BTM250WW

QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION
DMX	Address	A000-A512
	Channel Mode	2CH/3CH/5CH
STATIC	DIMMER	000-255
	STROBE	000-255
	ZOOM	000-255
PERSONALITY	Dim Curve	Linear
		Square Law
		INV Square Law
		S-Curve
	Dim Speed	OFF
		Low
		Medium
		High
	Frequency	1000Hz
		1200Hz
		1500Hz
		2000Hz
		4000Hz
		8000Hz
		16000Hz
		24000Hz
	Fan Mode	Full
		Auto
		Silent
	DMX Hold	Hold/Blackout
INFO	Version	Ver:xx.xx
	RDM UID	UID:
	Usage Time	Power On
		LED Total
	Temperature	Celsius
		Fahrenheit
RESET		Yes/No

DMX CHANNELS

2 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	MASTER DIMMER	000-255	Master Dimmer 0-100%
2	ZOOM	000-255	Zoom 0-100%

3 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	MASTER DIMMER	000-255	Master Dimmer 0-100%
2	FOCUS	000-255	Focus 0-100%
3	STROBE	000-255	Strobe slow to fast

5 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	MASTER DIMMER	000-255	Master Dimmer 0-100%
2	DIMMER FINE	000-255	Dimmer Fine
3	ZOOM	000-255	Zoom 0-100%
4	STROBE	000-255	Strobe slow to fast
5	DIMMER SPEED	000-030	Fade off
		031 - 060	Low
		061 - 090	Medium
		091 - 255	High



BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT

 **beamZ^{Pro}**

offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!



BEAMZLIGHTING.COM