



BEAMZ
MADE
EAZY

155.134_155.135 V1.0

SFP300T & SFP400T
QUICK **START GUIDE**

CONTROL MENU

MENU		DESCRIPTION
DMX ADDRESS	001-512	Press ENTER to edit. Use UP/DOWN to adjust. Press ENTER again to save.
CONTROL MODE	DMX	Slave mode: Receives DMX signals from console or master.
	Jump	Master mode: Auto-run and send DMX signals to slaves.
	Fade	
	Pulse	
	Sound	
	Manual	Master mode: Run manual data and send DMX signals to slaves.
Knob	Master mode: Run knob mode and send DMX signals to slaves.	
CHANNEL MODE	6CH/4CH/3CH/2CH	See channel table for details.
AUTO SPEED	Adjusts auto-run speed for Jump and Pulse modes.	0-100 (Slow-Fast)
MANUAL	Manual settings	See manual control section
DMX HOLD	ON	Maintain when there is no DMX signal
	OFF	Clear when there is no DMX signal
SCREEN FLIP	OFF	The screen displays normally
	ON	Inverts screen display.
LANGUAGE	CHINESE	Select display language.
	English	

MANUAL CONTROL

This interface controls the fixture directly (DMX signals are ignored).

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000-255	Master dimming
2	STROBE	000-255	Strobe speed
3	WARM WHITE	000-255	Warm white dimming
4	WHITE	000-255	White dimming

DMX CHANNELS

2 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000-255	Master dimming.
2	COLOR TEMPERATURE	000	No function.
		001-255	Color temperature adjustment (low to high).

3 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000-255	Master dimming.
2		000-255	Warm white dimming.
3		000-255	White dimming.

4 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000-255	Master dimming.
2		000-255	Warm white dimming.
3		000-255	White dimming.
4	STROBE SPEED	000	No function.
		001-255	Strobe speed adjustment (slow to fast).

6 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION		
1	DIMMER	000-255	Master dimming.		
2		000-255	Warm white dimming.		
3		000-255	White dimming.		
4	STROBE SPEED	000	No function.		
		001-255	Strobe speed adjustment (slow to fast).		
5	MACRO SPEED	000-255	Macro speed (slow to fast).		
		000-004	No function.		
		005-010	Color1		
		011-016	Color2		
		017-022	Color3		
		023-028	Color4		
		029-034	Color5		
		035-040	Color6		
		041-046	Color7		
		047-052	Color8		
		053-058	Color9		
		6	COLOR	059-064	Color10
				065-070	Color11
				071-076	Color12
				077-082	Color13
				083-088	Color14
089-094	Color15				
095-099	Color16				
100-149	Jump mode.				
150-199	Fade mode.				
200-249	Pulse mode.				
250-255	Sound mode.				



BEAMZ

**YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT**



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.

