



BEAMZ
MADE
EAZY

155.137_155.138 V1.0

SFP300C & SFP400C

QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION
DMX ADDRESS	001-512	Press the 'ENTER' button to enter editing mode. Press the "up" and "down" keys to change the address code. Press 'ENTER' again to exit editing mode
CONTROL MODE	DMX	Slave mode: Receives DMX signals from console or master
	Jump	Master mode: Auto-run and send DMX signals to slaves
	Gradient	
	Pulse	
	Sound	
	Manual	Master mode: Run manual data and send DMX signals to slaves
	Knob	Master mode: Run knob mode and send DMX signals to slaves
CHANNEL MODE	9CH/5CH/2CH	See channel table for details
AUTO SPEED	Adjusts auto-run speed	0-100 (Slow-Fast)
MANUAL	Manual settings	See manual control section
DMX HOLD	ON	Maintain when there is no DMX signal
	OFF	Clear when there is no DMX signal
SCREEN REVERSE	OFF	The screen displays normally
LANGUAGE	ON	Inverts screen display
	CHINESE	Select display language
	English	

MANUAL CONTROL

This interface controls the fixture directly (DMX signals are ignored).

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000-255	Master dimming
2	RED	000-255	Red dimming
3	GREEN	000-255	Green dimming
4	BLUE	000-255	Blue dimming
5	LIME	000-255	Lime dimming
6	AMBER	000-255	Amber dimming
7	STROBE	000-255	Strobe speed

DMX CHANNELS

2 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000-255	Master dimming.
2	STROBE	000	No function.
		001-255	Strobe, from slow to fast

5 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000-255	Red dimming, 0-100%
2		000-255	Green dimming, 0-100%
3		000-255	Blue dimming, 0-100%
4		000-255	Lime dimming, 0-100%
5		000-255	Amber dimming, 0-100%

9 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION		
1	DIMMER	000-255	Master dimming.		
2		000-255	Red dimming, 0-100%		
3		000-255	Green dimming, 0-100%		
4		000-255	Blue dimming, 0-100%		
5		000-255	Lime dimming, 0-100%		
6		000-255	Amber dimming, 0-100%		
7	STROBE	000	No function		
		001-255	Strobe, from slow to fast		
8	MACRO SPEED	000-255	Marco speed		
		000-004	No function		
		005-010	Color 1		
		011-016	Color 2		
		017-022	Color 3		
		023-028	Color 4		
		029-034	Color 5		
		035-040	Color 6		
		041-046	Color 7		
		047-052	Color 8		
		053-058	Color 9		
		9	MACRO	059-064	Color 10
				065-070	Color 11
				071-076	Color 12
				077-082	Color 13
				083-088	Color 14
089-094	Color 15				
095-099	Color 16				
100-149	Color jump				
150-199	Color gradient				
200-249	Color pulse				
250-255	Sound control				



BEAMZ

**YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT**



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.

