



BEAMZ
MADE
EAZY

152.120 V1.0

IGNITE740

QUICK START GUIDE

CONTROL MENU

| MENU | DESCRIPTION | | |
|----------------------|-------------------|---------------------------|---------|
| DMX ADDRESS | 000 - 512 | | |
| | DMX Mode | 17CH / 45CH | |
| FIXTURE | Run Mode | DMX / Auto/ Sound | |
| | Pan Invert | Close / Open | |
| | Tilt Invert | Close / Open | |
| | No Signal | Clear / Hold | |
| | Fan Control | Auto / Client / High | |
| | Dimmer Curve | Linear/Exp.2.0/Exp.1.5/S- | |
| | Sound Sensitivity | 000-099 | |
| | MANUAL | Pan | 000-255 |
| Pan Fine | | 000-255 | |
| Tilt | | 000-255 | |
| Tilt Time | | 000-255 | |
| ... | | ... | |
| INFORMATION | Temperature | Head Temp | xxx°C |
| | Software Version | Panel | Vx.xx |
| | | Dimmer | Vx.xx |
| FACTORY | Password | 000-255 | |
| | Pan | 000-255 | |
| | Tilt | 000-255 | |
| | Zoom | 000-255 | |
| | Red | 000-255 | |
| | Green | 000-255 | |
| | Blue | 000-255 | |
| | White | 000-255 | |
| FIXTURE RESET | Moter Reset | Off / Run | |
| | Factory | Off / Run | |
| DISPLAY | Language | CH / EN | |
| | Display Flip | Normal / Reverse | |
| | Display Mode | 60s / Show | |

DMX CHANNELS

| CHANNEL | FUNCTION | VALUE | DESCRIPTION |
|---------|----------|--------------|--|
| 17 CH | 45 CH | | |
| 1 | 1 | Pan | 000-255 Pan |
| 2 | 2 | Pan Fine | 000-255 Pan Fine |
| 3 | 3 | Tilt | 000-255 Tilt |
| 4 | 4 | Tilt Fine | 000-255 Tilt Fine |
| 5 | 5 | PT Speed | 000-255 PT Speed |
| 6 | 6 | Zoom | 000-255 Zoom |
| 7 | 7 | Dim | 000-255 0-100% dimmer from dark to brighter |
| | | | 000-003 OFF |
| | | | 004-103 Strobe from slow to fast |
| | | | 104-107 0n |
| | | | 108-207 Pulse strobe from slow to fast |
| 8 | 8 | Strobe | 208-212 0n |
| | | | 213-225 Random slow strobe |
| | | | 226-238 Random medium strobe |
| | | | 239-251 Random fast strobe |
| | | | 252-255 0n |
| 9 | 9 | Red | 000-255 Red dimmer |
| 10 | 10 | Green | 000-255 Green dimmer |
| 11 | 11 | Blue | 000-255 Blue dimmer |
| 12 | 12 | White | 000-255 White dimmer |
| | | | 000 Unused |
| | | | 001-027 8500K |
| | | | 028-055 7500K |
| | | | 055-083 6800K |
| | | | 084-111 6200K |
| 13 | 13 | CCT | 112-139 5600K |
| | | | 140-167 5000K |
| | | | 168-195 4500K |
| | | | 196-223 3600K |
| | | | 224-251 3200K |
| | | | 252-255 2800K |
| 14 | 14 | Macro | 000-255 Macro color |
| | | | 000 OFF |
| 15 | 15 | Effect | 001-255 Built-in dynamic effects, every 5 values have a effect |
| 16 | 16 | Effect Speed | 000-255 Effect speed |
| 17 | 17 | Reset | 000-250 No function |
| | | | 251-255 Motor reset after 5s |
| / | 18 | Red 1 | 000-255 Red 1 dimmer |
| / | 19 | Green 1 | 000-255 Green 1 dimmer |
| / | 20 | Blue 1 | 000-255 Blue 1 dimmer |
| / | 21 | White 1 | 000-255 White 1 dimmer |
| / | ... | ... | ... |
| / | 44 | Blue 7 | 000-255 Blue 7 dimmer |
| / | 45 | White 7 | 000-255 White 7 dimmer |



BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT



offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!

