



**BEAMZ**  
**MADE**  
**EAZY**

152.572 V1.0

**BRUTE 20000**

**QUICK **START** GUIDE**

# CONTROL MENU

MENU		DESCRIPTION	
<b>FUNCTION MODE</b>	DMX mode	Set in DMX mode	
	Auto mode	Set in automode	
<b>SHOW PLAY</b>	Auto run	Internal program 1-** Play a show list	
<b>PLAY SHOW</b>	Choose show	Internal program 1-** Play a specific show	
<b>PLAY SETUP</b>	Play speed	Select speed Default is 50%	
	Play mode	Loop play	
		Random play	
<b>ADDRESS SETUP</b>	Adress setup	Set DMX address	
<b>CHANNEL SETUP</b>	Normal Mode	Set DMX in 10CH mode	
	Expert Mode	Set DMX in 34CH mode	
<b>LASER SETUP</b>	Scanner Speed	Default setting 25kpps (Scanner speed can be set up to 40kpps. Pls set the correct speed, in case to fail the scanner.)	
	Color	Single	
		RGY	
		RBP	
		GBC	
		RGB (default setting)	
		WYPC	
	Laser (modulation)	Analog (default setting)	
		TTL	
	Invert	Normal	
		Invert X	
		Invert Y	
		Invert XY	
	Image Size	Size X	
		Size Y	
	Position Setup	Position X	
		Position Y	
<b>GENERAL SETUP</b>	Reset Default	ON/OFF	
	Safety protected	ON/OFF	one beam protection
	Master Setup	ON/OFF	
	Backlight	ON/OFF	When select OFF it will have a 15 seconds delay
	Display setup	Rotate 180 Deg	
		Normal	
	About system		

# DMX CHANNELS

## 10 CHANNEL MODE

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	ON/OFF	000	Laser off
		001-255	Laser ON (Brightness from 1% to 100%)
2	Strobe	001-255	Strobe speed, from slow to fast
3	Pattern size	000-255	Select pattern size
4	X axis position	000-255	Change X position, value 128 is the middle position (valid only when CH3 is selected 1-255)
5	Y axis position	000-255	Change Y position, value 128 is the middle position (valid only when CH3 is selected 1-255)
6	Choose show	000-255	Select a show for every 2 values (CH9 selected a show list)
7	Color	000-063	Select single color
		064-095	Fixed color/color changing effect speed selection
		096-127	Color changing effect speed selection
		128-159	Color changing effect speed selection/flowing color effect speed selection
		160-191	Flow color effect speed selection 1
		192-223	Flow color effect speed selection 2
		224-255	Color drawing effect speed selection
8	Line scanning	000-127	Scan speed selection
	Dot scanning	128-255	Scan speed selection
9	Show list	000-255	Select a show list every 8 values s (Value 0 selects all lists)
10	Auto Mode	000-026	Default running speed of Auto Mode
		027-255	Select running speed (from slow to fast)

# DMX CHANNELS

## 34 CHANNEL MODE

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	ON/OFF	000	Laser off
		001-255	Laser ON (Brightness from 1% to 100%)
2	Strobe	001-255	Strobe speed, from slow to fast
3	Pattern size	000-255	Select pattern size
4	X axis position	000-255	Change X position, value 128 is the middle position (valid only when CH3 is selected 1-255)
5	Y axis position	000-255	Change Y position, value 128 is the middle position (valid only when CH3 is selected 1-255)
6	Choose show	000-255	Select a show for every 2 values (CH9 selected a show list)
7	Color	000-063	Select single color
		064-095	Fixed color/color changing effect speed selection
		096-127	Color changing effect speed selection
		128-159	Color changing effect speed selection/flow color effect speed selection
		160-191	Flow color effect speed selection 1
		192-223	Flow color effect speed selection 2
		224-255	Color drawing effect speed selection
8	Line scanning	000-127	Scan speed selection
	Dot scanning	128-255	Scan speed selection
9	Show list	000-255	Select a show list every 8 values s (Value 0 selects all lists)
10	Auto Mode	000-026	Default running speed of Auto Mode
		027-255	Select running speed (from slow to fast)
11	Z rotation	001-127	Select rotation angle
		128-255	Select rotation speed
12	X rotation	001-127	Select rotation angle
		128-255	Select rotation speed
13	Y rotation	001-127	Select rotation angle
		128-255	Select rotation speed
14	X moving	001-127	Select moving position
		128-255	Select moving speed
15	Y moving	001-127	Select moving position
		128-255	Select moving speed
16	Zooming	001-127	Select zooming size
		128-255	Select zooming speed
17	Drawing	001-255	Select drawing speed
18	X wave	001-127	Select X waving speed
	Y wave	128-255	Select Y waving speed
<b>Channel 19-34 is valid for patter 2 (channel 26 to choose a show list, and channel 23 to choose a show)</b>			
19	Strobe	001-255	Strobe speed, from slow to fast
20	Pattern size	000-255	Select pattern size
21	X axis position	000-255	Change X position, value 128 is the middle position (valid only when CH3 is selected 1-255)
22	Y axis position	000-255	Change Y position, value 128 is the middle position (valid only when CH3 is selected 1-255)
23	Choose show	000-255	Select a show for every 2 values (CH26 selected a show list)

<b>24</b>	Color	000-063	Select single color
		064-095	Fixed color/color changing effect speed selection
		096-127	Color changing effect speed selection
		128-159	Color changing effect speed selection/flow color effect speed selection
		160-191	Flow color effect speed selection
		192-223	Flow color effect speed selection
		224-255	Color drawing effect speed selection
<b>25</b>	Line scanning	000-127	Scan speed selection
	Dot scanning	128-255	Scan speed selection
<b>26</b>	Show list	000-255	Select a show list every 8 values s (Value 0 selects all lists)
<b>27</b>	Z rotation	001-127	Select rotation angle
		128-255	Select rotation speed
<b>28</b>	X rotation	001-127	Select rotation angle
		128-255	Select rotation speed
<b>29</b>	Y rotation	001-127	Select rotation angle
		128-255	Select rotation speed
<b>30</b>	X moving	001-127	Select moving position
		128-255	Select moving speed
<b>31</b>	Y moving	001-127	Select moving position
		128-255	Select moving speed
<b>32</b>	Zooming	001-127	Select zooming size
		128-255	Select zooming speed
<b>33</b>	Drawing	001-255	Select drawing speed
<b>34</b>	X wave	001-127	Select X waving speed
	Y wave	128-255	Select Y waving speed







# BEAMZ

**YOUR FUTURE**  
**YOUR SKILLS**  
**YOUR PLATFORM**  
**YOUR PARTY**  
**YOUR EVENT**



offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!

