



BEAMZ
MADE
EAZY

153.862 V1.1

SHIMMER 4

QUICK START GUIDE

DMX CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Strobe LED dimming	000-255	White 0°-100%
2		000-255	From slow Purple 0°-100%
3	Strobe	000-007	Strobe NO function
		008-255	The strobe from slow to fast (purple light is always bright)
4	Magic ball color macro definition	000-005	No function
		006-014	Red
		015-028	Red+Green
		029-042	Green
		043-056	Green+Blue
		057-070	Blue
		071-084	Blue+White
		085-098	White
		099-112	Red+White
		113-126	Green+White
		127-140	Red+Blue
		141-154	Green+Blue+White
		155-168	Red+Green+Blue
		169-182	Red+Blue+White
		183-196	Red+Green+White
		197-209	Red+Green+Blue+White
		210-250	The magic ball jumps from slow to fast
		251-255	Magic ball strobe
5	Magic ball motor	000-127	Motor bij 0° to 160° Revolve
		128-255	Rotate from slow to fast
6	Pattern color macro definition	000-005	No function
		006-014	Red
		015-028	Red+Green
		029-042	Green
		043-056	Green+Blue
		057-070	Blue
		071-084	Blue+White
		085-098	White
		099-112	Red+White
		113-126	Green+White
		127-140	Red+Blue
		141-154	Green+Blue+White
		155-168	Red+Green+Blue
		169-182	Red+Blue+White
		183-196	Red+Green+White
		197-209	Red+Green+Blue+White
		210-250	No function
		251-255	Pattern Strobe
7	Pattern motor	000-004	Stop
		005-127	Rotate clockwise from slow to fast
		128-133	Stop
		134-255	Counterclockwise from slow to fast
8	Laser color control	000-002	Empty
		003-063	Red
		064-127	Green

		128-191	Red + Green
		192-255	Red and Green alternate from slow to fast
9	Laser motor	000-004	Stop
		005-127	Rotate clockwise from slow to fast
		128-133	Stop
		134-255	Counterclockwise rotation from slow to fast
10	Dimmer	000-255	Red 0-100%
11		000-255	Green 0-100%
12		000-255	Blue 0-100%
13		000-255	White 0-100%
14		000-015	Effective dyeing and dimming
		016-075	Dyeing jumps from slow to fast
		076-135	Dyeing gradient, from slow to fast
		136-195	The chromatin changes from slow to fast
		196-255	Dyeing strobe, from slow to fast
15	Built-in program	000-010	Empty
		011-110	Built-in program 1
		111-210	Built-in program 2
		211-235	Voice control triggers the built-in program 1
		236-255	Voice control triggers the built-in program 2
16	Built-in program speed	000-255	The built-in program changes from slow to fast

Design and product specifications are subject to change without prior notice.

The products referred to in this manual conform to the European Community Directives to which they are subject:

European Union

Tronios B.V.,
Bedrijvenpark Twente Noord 18,
7602KR Almelo, The Netherlands

2014/35/EU
2014/30/EU
2011/65/EC



United Kingdom

Tronios Ltd.,
130 Harley Street,
London W1G 7JU, United Kingdom

S.I. 2016:1101
S.I. 2016:1091
S.I. 2012:3032





BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.



BEAMZLIGHTING.COM