



155.110\_150.114 V1.1

**BTM100TW & BTM250TW**

**QUICK START GUIDE**

# CONTROL MENU

| MENU      |              |             | DESCRIPTION              |
|-----------|--------------|-------------|--------------------------|
| DMX       | Address      | A000-A512   | DMX address setting      |
|           | Channel Mode |             | 3CH/4CH/6CH              |
| STATIC    | CCT          | 2700K-6500K | Static CCT Control       |
|           | Dimmer       | 000-255     | Dimmer                   |
|           | Strobe       | 000-255     | Strobe form slow to fast |
|           | Zoom         | 000-255     | Zoom 0-100%              |
|           | PERSONALITY  | Dim Curve   |                          |
|           |              |             | Square Law               |
|           |              |             | INV Square Law           |
|           |              |             | S-Curve                  |
| Dim Speed |              |             | OFF                      |
|           |              |             | Low                      |
|           |              |             | Medium                   |
|           |              |             | High                     |
| Frequency |              |             | 1000Hz                   |
|           |              |             | 1200Hz                   |
|           |              |             | 1500Hz                   |
|           |              |             | 2000Hz                   |
|           |              |             | 4000Hz                   |
|           |              |             | 8000Hz                   |
|           |              |             | 16000Hz                  |
|           |              |             | 24000Hz                  |
| Fan Mode  |              |             | Full                     |
|           |              |             | Auto                     |
|           |              |             | Silent                   |
| DMX Hold  |              |             | Hold/Blackout            |
| INFO      | Version      |             | Ver:xx.xx                |
|           | RDM UID      | UID:        |                          |
|           | Usage Time   |             | Power On                 |
|           |              |             | LED Total                |
|           | Temperature  |             | Celsius                  |
|           |              |             | Fahrenheit               |
| RESET     |              |             | Yes/No                   |

## DMX CHANNELS

### 3 CHANNELS

| CHANNELS | FUNCTION      | VALUE   | DESCRIPTION          |
|----------|---------------|---------|----------------------|
| 1        | MASTER DIMMER | 000-255 | Master Dimmer 0-100% |
| 2        | CCT           | 000-255 | 2700K-6500K          |
| 3        | ZOOM          | 000-255 | Zoom 0-100%          |

### 4 CHANNELS

| CHANNELS | FUNCTION      | VALUE   | DESCRIPTION              |
|----------|---------------|---------|--------------------------|
| 1        | MASTER DIMMER | 000-255 | Master Dimmer 0-100%     |
| 2        | CCT           | 000-255 | 2700K-6500K              |
| 3        | ZOOM          | 000-255 | Zoom 0-100%              |
| 4        | STROBE        | 000-255 | Strobe from slow to fast |

### 6 CHANNELS

| CHANNELS | FUNCTION      | VALUE   | DESCRIPTION              |
|----------|---------------|---------|--------------------------|
| 1        | MASTER DIMMER | 000-255 | Master Dimmer 0-100%     |
| 2        | DIMMER FINE   | 000-255 | Dimmer Fine              |
| 3        | CCT           | 000-255 | 2700K-6500K              |
| 4        | ZOOM          | 000-255 | Zoom form 0-100%         |
| 5        | STROBE        | 000-255 | Strobe from slow to fast |
| 6        | DIMMER SPEED  | 000-030 | Fade off                 |
|          |               | 031-060 | Low                      |
|          |               | 061-090 | Medium                   |
|          |               | 091-255 | High                     |



# BEAMZ

**YOUR FUTURE**  
**YOUR SKILLS**  
**YOUR PLATFORM**  
**YOUR PARTY**  
**YOUR EVENT**

 **beamZ<sup>Pro</sup>**

offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!



**BEAMZLIGHTING.COM**